

USING YOUR BEATSTEP PRO WITH ABLETON

# BEATSTEP PRO

#### Dear Musician,

**Congratulations** on your purchase of Arturia BeatStep Pro. BeatStep Pro is the combination of a pad/knob MIDI controller and a versatile standalone sequencer.

BeatStep Pro can be configured and used in many different ways. We can not list them all here, but we can try and give you a few examples in this quickstart.

Musically Yours,

The Arturia Team

## O1

BEAISTEP PRO AS A	
SLAVE IN ABLETON	

a. Setting up your Beatstep Pro	p.O2
b. Setting up Ableton (part 1)	p.O2
c. Setting up Ableton (part 2)	p.03
d. Let's play	p.03

BEATSTEP PRO AS A MIDI CONTROLLER IN LIVE

a. Setting up your Beatstep Pro	p.06
b. Setting up Ableton	p.06
c. Let's play	p.06

### BEATSTEP PRO AS A MASTER MIDI CLOCK

a. Setting up your Beatstep Pro	p.O
b. Setting up Ableton (part 1)	p.O
c. Setting up Ableton (part 2)	p.O
d Let's plau	n O!



## CONTROLLING LIVE WITH THE MCU PROTOCOL

a. Setting up your Beatstep Pro \_\_\_\_ p.07 b. Setting up Ableton \_\_\_\_\_ p.07



## **1. BEATSTEP PRO AS A SLAVE IN ABLETON**

#### a. Setting up your Beatstep Pro

First, to make sure the Beatstep Pro will play at the same tempo as Live, and will respond to Start & Stop messages, set the "Sync" mode to "USB".



#### b. Setting up Ableton (part 1)

Navigate to Ableton's Midi preferences, set the first "Input" line corresponding to the Beatstep Pro so that "Track" is set to "On", and the first "Output" line corresponding to the Beatstep Pro so that "Sync" is set to "On"

al	Control Surface	Input	Outpu	t
	1 None	None 🔻	None	T (Dump)
dio	2 None	None 🔻	None	▼ (Dump)
	3 None T	None 🔻	None	▼ (Dump)
DI	4 None	None 🔻	None	<ul> <li>Dump</li> </ul>
nc	5 None *	None 🔻	None	Dump
	6 None T	None V	None	▼ (Dump)
ider	Takeover Mode	None	]	
to and	MIDI	Ports	Track S	ync Remote
		Ports ItStep Pro (Arturia Beat		Off Off
rp	D Input: Arturia Bea		Ste On	
cord Irp unch	▷ Input: Arturia Bea ▷ Input: Arturia Bea	tStep Pro (Arturia Beat		Off Off
rp	<ul> <li>▷ Input: Arturia Bea</li> <li>▷ Input: Arturia Bea</li> <li>▷ Output: Arturia Bea</li> </ul>	itStep Pro (Arturia Beat itStep Pro (BeatStepPro	Ste On Ste Off	10 10



#### c. Setting up Ableton (part 2)

Create a new MIDI track (or instrument track), and set the input to receive midi from "Arturia Beatstep Pro (Arturia Beatstep Pro) and set the channel accordingly to the sequence you want to get from the Beatstep.

By default, the Beatstep Pro Sequencer 1 sends notes to MIDI channel 1, the Sequencer 2 sends notes to MIDI channel 2, and Drum sequencer sends midi to MIDI channel 10.

Here in the picture, Channel 1 is selected, this means the created track will receive notes from the Sequencer 1 of the Beatstep Pro.

MIDI From		
Arturia BeatStep Pro (Arturia BeatStepPro)	•	
I Ch. 1	•	
Monitor		
In Auto Off	_	
Audio To		

After this, enable record arm for your track to make sure it receives MIDI from the Beatstep Pro.



#### d. Let's Play !

Write a sequence on your Beatstep Pro, and press play on Ableton Live. You should be able to hear the notes played from the Beastep Pro if you have a VST instrument inserted into your track !





## 2. BEATSTEP PRO AS A MASTER MIDI CLOCK

#### a. Setting up your Beatstep Pro

First, to make sure Ableton will play at the same tempo as the Beatstep Pro, and will respond to Start & Stop messages, set the "Sync" mode to "Int".



#### b. Setting up Ableton (part 1)

Navigate to Ableton's Midi preferences, set the first "Input" line corresponding to the BeatStep Pro so that "Track" & "Sync" are set to "On". Leave the "Output" lines greyed out.

[Good to know : If you have other MIDI devices in your setup and want them to follow the BeatStep Pro's clock, set their "Output" line so that "Sync" is set to "On" for them too.]

		Contra	ol Surface	Input		Out	put .	
	1 1	ione		None		None		· (Dump
6	2 5	ione		None	•	None	10	· Cours
	3.5	ione		None		None		<ul> <li>Oump</li> </ul>
	4 5	ione		None	•	None		<ul> <li>Course</li> </ul>
ŧ	5 5	ione		None		None		<ul> <li>Ours</li> </ul>
	6 5	ione		None	•	None		<ul> <li>Oursy</li> </ul>
<b>1</b>			MICL	Cortis		Track	Sync	Remote
ed .	DR	nput	Arturia Beatt	Hep Pro (Arturi	a BeatSt	On	On	Off
p hch	DB	nput	Arturia Deat	Hop Pro (Beats	RepPro I	Off	01	0#
	0.0		Arturia Beat	Rep Pro (Arturi	a BeatSt	NO I	Off	Of
	DO	Judput	Arturia Deat	Rep Pro (Beats	RepProt	NO I	Off	Of I



#### c. Setting up Ableton (part 2)

In your main Ableton window, activate the "EXT" button at the top left of the screen. It will tell Ableton to follow the clock you just set in the preferences, meaning Ableton will play as soon as you hit the Play button on the Beatstep Pro, and it will also follow the clock/tempo from the Beatstep Pro.



#### d. Let's Play !

If the settings were made right, Ableton's tempo indicator will be greyed out, and will sync with the Beatstep Pro clock.





## 3. BEATSTEP PRO AS A MIDI CONTROLLER IN LIVE

#### a. Setting up your Beatstep Pro

First, to make sure BeatStep Pro will send MIDI CCs to Ableton Live; set it to Control Mode by clicking on the Control Mode button on the BeatStep Pro.



#### b. Setting up Ableton (part 1)

Navigate to Ableton's Midi preferences, set the first "Input" line corresponding to the BeatStep Pro so that "Track" & "Remote" are set to "On".

loci		Contr	ol Surface	Input		Out	tput	
	1	None		None		None		• Dump
udio	2	None		None	•	None		• Dump
	3	None		None	•	None	_	• Dump
AIDI	4	None	-	None	•	None		• Dump
lync	5	None		None	•	None		• Dump
the little	6	None		None		None		• Dump
folder		Take	over Mode	None	۷			
ibrary								
			MIDI	hortes		Track	Sync	Remote
lecord		Input:		Porta Step Pro (Arturi	a BeatS		Sync Off	Remote
ecord /arp		Input:	Arturia Beat			On	-	
lecord Varp aunch	D	Input	Arturia Beat	Step Pro (Arturi	itepPro		01	On
ecord Aarp aunch	D D	Input: Output:	Arturia Beat! Arturia Beat! Arturia Beat!	Step Pro (Arturi Step Pro (Beats	itepPro		01	On Off
Library Record Warp Launch CPU Licenses	D D	Input: Output:	Arturia Beat! Arturia Beat! Arturia Beat!	Step Pro (Arturi Step Pro (Beats Step Pro (Arturi	itepPro		Off	0n 0f

#### c. Let's Play !

If the settings were made right, you will now be able to assign the BeatStep's Pro knobs & buttons to control parameters within Ableton Live.



## 4. CONTROLLING LIVE WITH THE MCU PROTOCOL

#### a. Setting up your BeatStep Pro

First check that your BeatStepPro is set on Mackie Control mode and not on HUI mode in the global parameter of the MidiControlCenter.



Set your BeatStepPro in control mode and press "knobs" button to enable MCU/HUI on the device

#### b. Setting up Ableton

Navigate to Ableton's Midi preferences, set Control Surface type on MackieControl. Then select "Arturia BeatStepPro (Port2) as input and output. If you're on a Mac you should select BeatStepPro OutEditor as Input and BeatStepProInEditor as output.

			Pr	references		
Look		Control Surfa	ce	Input	Output	-
1	1	MackieControl	•	Arturia BeatStep Piv	Arturia BeatStep PIT	Dump
Audio	2	None	•	None *	MIDI 1 x 1	Dump
	3	None	•	None •	None 🔻	Dump
MIDI	- 4	None	•	None	None 🔻	Dump
Sync	5	None	Ŧ	None 🔻	None 🔻	Dump
File	6	None	•	None	None 🔻	Dump